



## SBU34060GE2DL13

Huawei® Compatible 1000Base-BX SFP Transceiver (SMF, 1310nmTx/1490nmRx, 60km, LC, DOM, -40 to 85C)

### Product Description

This Huawei® SFP transceiver provides 1000Base-BX throughput up to 60km over single-mode fiber (SMF) using a wavelength of 1310nmTx/1490nmRx via an LC connector. It is guaranteed to be 100% compatible with the equivalent Huawei® transceiver. This easy to install, hot swappable transceiver has been programmed, uniquely serialized and data-traffic and application tested to ensure that it will initialize and perform identically. Digital optical monitoring (DOM) support is also present to allow access to real-time operating parameters. We stand behind the quality of our products and proudly offer a limited lifetime warranty.

Skylane's transceivers are RoHS compliant and lead-free.

### Features:

- INF-8074 and SFF-8472 Compliance
- Simplex LC Connector
- Industrial Temperature -40 to 85 Celsius
- Single-mode Fiber
- Hot Pluggable
- Excellent ESD Protection
- Metal with Lower EMI
- RoHS Compliant and Lead Free



### Applications:

- 1000Base-BX Ethernet
- Access (FTTx) and Enterprise
- 1x Fibre Channel

---

*For your product safety, please read the following information carefully before any manipulation of the transceiver:*



#### ESD

This transceiver is specified as ESD threshold 1kV for SFI pins and 2kV for all others electrical input pins, tested per MIL-STD-883G, Method 3015.4 /JESD22-A114-A (HBM). However, normal ESD precautions are still required during the handling of this module.



#### LASER SAFETY

This is a Class1 Laser Product according to IEC 60825-1:2007. This product complies with 21 CFR 1040.10 and 1040.11 except for deviations pursuant to Laser Notice No. 50, dated (June 24, 2007).

*The optical ports of the module need to be terminated with an optical connector or with a dust plug in order to avoid contamination.*

## Regulatory Compliance

- ESD to the Electrical PINs: compatible with MIL-STD-883E Method 3015.4
- ESD to the LC Receptacle: compatible with IEC 61000-4-3
- EMI/EMC compatible with FCC Part 15 Subpart B Rules, EN55022:2010
- Laser Eye Safety compatible with FDA 21CFR, EN60950-1& EN (IEC) 60825-1,2
- RoHS compliant with EU RoHS 2.0 directive 2015/863/EU

## Absolute Maximum Ratings

| Parameter                  | Symbol          | Minimum |    | Maximum | Unit |
|----------------------------|-----------------|---------|----|---------|------|
| Storage Temperature        | T <sub>S</sub>  | -40     |    | 85      | °C   |
| Relative Humidity          | RH              | 5       |    | 95      | %    |
| Supply Voltage             | V <sub>CC</sub> | -0.5    |    | 4.0     | V    |
| Operating Case Temperature | T <sub>c</sub>  | -40     | 25 | 85      | °C   |
| Data Rate                  |                 | 0.1     |    | 1.25    | Gb/s |

## Electrical Characteristics

| Parameter                                                               | Symbol          | Minimum | Typical | Maximum         | Unit  | Notes |
|-------------------------------------------------------------------------|-----------------|---------|---------|-----------------|-------|-------|
| Module Supply Current                                                   | I <sub>CC</sub> |         |         | 300             | mA    |       |
| Supply Voltage                                                          | V <sub>CC</sub> | 3.135   | 3.3     | 3.465           | V     |       |
| Power Dissipation                                                       | P <sub>D</sub>  |         |         | 1000            | mW    |       |
| Transmitter Differential Input Voltage (TD +/-)                         |                 | 300     |         | 2200            | mVp-p | 1     |
| Receiver Differential Output Voltage (RD +/-)                           |                 | 600     |         | 1200            | mVp-p | 2     |
| Low Speed output: Transmitter Fault (TX_FAULT)/ Loss of Signal (LOS)    | VOH             | 2.0     |         | V <sub>CC</sub> | V     | 3     |
|                                                                         | VOL             | 0       |         | 0.8             | V     |       |
| Low speed input: Transmitter Disable (TX_DISABLE), MOD_DEF 1, MOD_DEF 2 | VIH             | 2.0     |         | V <sub>CC</sub> | V     | 4     |
|                                                                         | VIL             | 0       |         | 0.8             | V     |       |

## Notes:

1. Internally AC coupled and terminated to 100 differential load
2. Internally Accoupled, but requires a 100 differential termination or internal to Serializer/Deserializer
3. Pulled up externally with a 4.7K- 10K resistor on the host board to V<sub>CC</sub>T,R.
4. MOD\_Def1 and Mod\_Def2 must be pulled up externally with a 4.7K-10K resistor on the host board to V<sub>CC</sub>T,R.

## Optical Characteristics

| Parameter                   | Symbol                                       | Minimum | Typical | Maximum | Unit | Notes |
|-----------------------------|----------------------------------------------|---------|---------|---------|------|-------|
| Transmitter                 |                                              |         |         |         |      |       |
| Launch Optical Power        | P <sub>o</sub>                               | 0       |         | 5       | dBm  |       |
| Center Wavelength Range     | λ <sub>c</sub>                               | 1260    | 1310    | 1360    | nm   |       |
| Extinction Ratio            | EX                                           | 9       |         |         | dB   |       |
| Spectral Width (-20dB)      | Δλ                                           |         |         | 1       | nm   |       |
| Side Mode Suppression Ratio | SMSR                                         | 30      |         |         | dB   |       |
| Optical Rise/Fall Time      | T <sub>rise</sub> /T <sub>fall</sub>         |         |         | 260     | ps   |       |
| Pout @TX-Disable Asserted   | P <sub>off</sub>                             |         |         | -45     | dBm  |       |
| Insertion Loss              | IL                                           |         | 0.35    |         | dB   |       |
| Eye Diagram                 | IEEE Std 802.3-2005 1000BASE-BX-U compatible |         |         |         |      |       |
| Receiver                    |                                              |         |         |         |      |       |
| Wavelength Range            |                                              | 1470    | 1490    | 1600    | nm   |       |
| Receiver Sensitivity        | S                                            |         |         | -26     | dBm  | 1     |
| Receiver Overload           | P <sub>OL</sub>                              | 0       |         |         | dBm  | 1     |
| Optical Return Loss         | ORL                                          | 12      |         |         | dB   |       |
| LOS De-Assert               | LOSD                                         |         |         | -24     | dBm  |       |
| LOS Assert                  | LOSA                                         | -35     |         |         | dBm  |       |
| LOS Hysteresis              |                                              | 0.5     | 3       | 5       | dB   |       |

### Notes:

1. Measured with PRBS 2<sup>7</sup>-1 test pattern, 1.25Gb/s, EX=9dB, BER<10<sup>-12</sup>.

## Timing Characteristic

| Parameter                                    | Symbol                | Minimum | Typical | Maximum | Unit | Notes |
|----------------------------------------------|-----------------------|---------|---------|---------|------|-------|
| Tx_disable assert time                       | T <sub>off</sub>      |         |         | 10      | us   |       |
| Tx_disable negate time                       | T <sub>on</sub>       |         |         | 1       | ms   |       |
| Time to initialize,include reset of TX_FAULT | T <sub>init</sub>     |         |         | 300     | ms   |       |
| TX_FAULT from the fault to assertion         | T <sub>fault</sub>    |         |         | 100     | us   |       |
| TX_disable time to start reset               | T <sub>reset</sub>    | 10      |         |         | us   |       |
| Receiver LOS Assert Time (on to off)         | T <sub>D,RX_LOS</sub> |         |         | 80      | us   |       |
| Receiver LOS Assert Time (off to on)         | T <sub>A,RX_LOS</sub> |         |         | 80      | us   |       |
| Serial I2C Clock Rate                        | I2C_Clock             |         |         | 100     | kHz  |       |

## Pin Descriptions

| Pin | Symbol      | Name/Descriptions                                                              | Engagement order (insertion) | Notes |
|-----|-------------|--------------------------------------------------------------------------------|------------------------------|-------|
| 1   | VeeT        | Transmitter Ground                                                             | 1                            |       |
| 2   | TX Fault    | Transmitter Fault Indication                                                   | 3                            | 1     |
| 3   | TX Disable  | Transmitter Disable-Module disables on high or open                            | 3                            | 2     |
| 4   | MOD-DEF2    | 2-Wire Serial Interface Data Line (Same as MOD-DEF2 in INF-8074i). LVTTTL-I/O. | 3                            | 3     |
| 5   | MOD-DEF1    | 2-Wire Serial Interface Data Line (Same as MOD-DEF2 in INF-8074i). LVTTTL-I.   | 3                            | 3     |
| 6   | MOD-DEF0    | Module Absent, Connect to VeeT or VeeR in Module.                              | 3                            | 3     |
| 7   | Rate Select | Not connected                                                                  | 3                            |       |
| 8   | LOS         | Loss of Signal.                                                                | 3                            | 4     |
| 10  | VeeR        | Receiver Ground                                                                | 1                            |       |
| 11  | VeeR        | Receiver Ground                                                                | 1                            |       |
| 12  | RD-         | Inverse Received Data out                                                      | 3                            | 5     |
| 13  | RD+         | Received Data out                                                              | 3                            | 5     |
| 14  | VeeR        | Receiver Ground                                                                | 1                            |       |
| 15  | VccR        | Receiver Power- +3.3V±5%                                                       | 2                            | 6     |
| 16  | VccT        | Transmitter Power- - +3.3 V±5%                                                 | 2                            | 6     |
| 17  | VeeT        | Transmitter Ground                                                             | 1                            |       |
| 18  | TD+         | Transmitter Data In                                                            | 3                            | 7     |
| 19  | TD-         | Inverse Transmitter Data In                                                    | 3                            | 7     |
| 20  | VeeT        | Transmitter Ground                                                             | 1                            |       |

### Notes:

- TX Fault is open collector/drain output which should be pulled externally with a 4.7K-10K resistor on the host board to supply < VccT +0.3V or VccR + 0.3V. When high, this output indicates a laser fault of some kind. Low indicates normal operation. In the low state, the output will be pulled to <0.8V.
- TX Disable input is used to shut down the laser output per the state table below. It is pulled up within the module with a 4.7K-10K resistor.

|                        |                      |
|------------------------|----------------------|
| Low (0-0.8V):          | Transmitter on       |
| Between (0.8V and 2V): | Undefined            |
| High (2.0-VccT):       | Transmitter Disabled |
| Open:                  | Transmitter Disabled |
- Mod-Def 0,1,2. These are the module definition pins. They should be pulled up with a 4.7K-10K resistor on the host board to supply less than VccT+0.3V or VccR+0.3V.  
Mod-Def 0 is grounded by the module to indicate that the module is present.  
Mod-Def 1 is clock line of two wire serial interface for optional serial ID.

Mod-Def 2 is data line of two wire serial interface for optional serial ID.

4. LOS (Loss of Signal) is an open collector/drain output which should be pulled up externally with a 4.7K - 10K resistor on the host board to supply  $<V_{ccT}+0.3V$  or  $V_{ccR}+0.3V$ . When high, this output indicates the received optical power is below the worst-case sensitivity (as defined by the standard in use). Low indicates normal operation. In the low state, the output will be pulled to  $<0.8V$ .
5. RD-/+ : These are the differential receiver outputs. They are AC coupled 100 differential lines which should be terminated with 100 differential at the user SERDES. The AC coupling is done inside the module and thus not required on the host board.
6. VccR and VccT are the receiver and transmitter power supplies. They are defined as  $3.3V \pm 5\%$  at the SFP connector pin. The in-rush current will typically be no more than 30mA above steady state supply current after 500ns.
7. TD-/+ : These are the differential transmitter inputs. They are AC coupled differential lines with 100 differential termination inside the module. The AC coupling is done inside the module and is thus not required on host board.






Diagram of Host Board Connector Block Pin Numbers and Names


Recommended Application Interface Circuit



Required Host Board Components




Mechanical Specifications



Unit:mm

Digital Diagnostic Memory Map



# About Skylane Optics

Skylane is a leading provider of transceivers for optical communication.

We offer an extensive portfolio for the enterprise, access, datacenter and metropolitan fiber optical market as well as for smart home applications and home networks.

We cover the European, South American and North American market with a strong partner network and have offices in Belgium, Brazil, Sweden and USA.

Our offerings are characterized by high quality and performance. In combination with our strong technical support, we enable our customers to build cost optimized network solutions.

We offer an extensive range of high-quality products including transceivers (Optical and copper), Active Optical Cable (AOC), Direct Attach Cable (DAC), Mux/Demux, Coding Box.

